

1. Introduction

Thank You for purchasing the ADSL Nation AMX-64. Please take a few moments to follow these simple instructions to get-online quickly and easily.

Package Contents

AMX-64 ADSL 4 port Gateway
12v UK Mains Adaptor
Telephone cable.

Hardware Installation

Connect the Mains Adapter to the power inlet and the mains power outlet. Switch on the AMX-64 using the power switch at the back of the unit. The red power LED should be illuminated on the front of the unit. After a few seconds the ready light will flash to indicate that the router is running, this flashing light is called the heartbeat.

Plug one end of the telephone cable in to the AMX-64 and the other to the phone line. The AMX-64 does not require a splitter, however you will still require microfilters/splitters for your other telephone equipment. If your ADSL service has been enabled and your connection is working the green showtime LED will stay on.

Use an Ethernet cable to connect the Router to the Hub/Switch on your LAN or to your Computer directly. Use a standard RJ45 Ethernet cable or crossover, the AMX-64 will automatically detect what type of cable is in use.

IMPORTANT !

Before beginning configuration, please DISABLE any Personal firewall software you may be using as it may interfere with the installation process

2. Networking


The AMX-64 will automatically configure each computer on the network. In order to do this each computer's network settings must be set to use DHCP or Automatic configuration.

Windows 2000 & XP

1. Click Start button, Settings and choose "Network & Dial-up Connections".
2. Double click Network Adapter icon and click properties.

Select the Internet Connection TCP/IP item from the list and click Properties.

Make sure that "Obtain IP address automatically" is selected and click apply.



Windows 95 & 98


1. Click Start button, Settings and choose Control Panel.
2. Double click Network icon and select Configuration tab.

Select the TCP/IP line that has been associated with your network card in the Configuration tab and click Properties.

Make sure that "Obtain IP address automatically" is selected and click apply.

MacOS X

1. Open the System Preferences utility and click on the network icon.
2. Make sure your network card is selected usually "built-in Ethernet" and set configure using DHCP. Click on Apply Now to complete.



MacOS 9

1. Open the TCP/IP control panel. You can find it in the Apple Menu under the folder "Control Panels."
2. Make sure your network card is selected usually "built-in Ethernet" and set configure using DHCP. Close the window and save changes if prompted.


PLEASE REBOOT THE COMPUTER - FOR CHANGES TO TAKE EFFECT

3. Configuration

The AMX-64 offers a web-based (HTML) graphical user interface allowing users to manage the Router using a standard browser such as Netscape Navigator or Microsoft Internet Explorer.

Accessing the Web Manager

1. Launch the Web browser.
2. Enter the LAN port default IP address `http://10.0.0.2` in to the browser.



3. The user name and password prompt will appear. Enter the default login User Name and Password.

Default login details

User Name: **admin**
Password: **password**

The user name and password prompt may take up to 1 min. the first time the AMX-64 is accessed.

Quick & Easy Setup



AMX-64 Internet Gateway - Web Configuration



Quick & Easy Setup

Configure your AMX-64 using one of the default configurations.



Advanced Setup

Configure advanced functions such as Port Forwarding and DHCP.

Thank you for purchasing the ADSL Nation AMX-64 Internet Gateway.

Click "Quick & Easy Setup" to begin the guided set-up. Follow the on-screen instructions.



AMX-64 Internet Gateway - Web Configuration

3

Quick & Easy Setup

Configuration complete please click save to apply changes.
-The AMX-64 will reboot-

Summary Of Configuration

WAN

Protocol: PPP Over ATM Encapsulation: VC Mux
VPI: 0 VCI: 38
IP Address: Assigned by ISP
Subnet Mask: Assigned by ISP
Default Gateway: Assigned by ISP

LAN

Nat Configuration: NAPT
Router LAN IP: 10.0.0.2 (Default Gateway for PC's)
Subnet Mask: 255.255.255.0
DHCP Server: Enabled

UNDO SAVE

ADSL Nation AMX-64 Internet Gateway - Click Save To Apply.

IMPORTANT

When the configuration is complete and the AMX-64 reboots, you will hear a clicking sound. As a result of the reboot your browser will display a blank screen, waiting for a new page to load. This is normal behaviour. After approximately 10 seconds click the stop button on the browser and the set-up is complete.



Start Here



AMX-64 Quick Start Guide

www.adslnation.com